

# synapse-haproxy container in CrashLoopBackOff state

## Issue

We are seeing

```
[karl1@element ~]$ kubectl get pods -n element-onprem
```

NAME	READY	STATUS	RESTARTS	AGE
server-well-known-8c6bd8447-fts78	1/1	Running	2	39h
app-element-web-c5bd87777-745gh	1/1	Running	2	39h
postgres-0	1/1	Running	2	39h
instance-synapse-haproxy-5b4b55fc9c-jv7pp	0/1	CrashLoopBackOff	40	39h
instance-synapse-main-0	1/1	Running	6	39h

and the synapse-haproxy container never leaves the `CrashLoopBackOff` state.

## Environment

- Red Hat Enterprise Linux 8.5
- Element Enterprise On-Premise PoC Installer 0.6.1

## Resolution

Add the following lines to `/etc/security/limits.conf`:

```
*      soft  nofile 100000
*      hard  nofile 100000
```

and reboot the box. After a reboot, the microk8s environment will come back up and the synapse-haproxy container should run without error.

# Root Cause

Check the logs of synapse-haproxy with this command:

```
kubectl logs -n element-onprem instance-synapse-haproxy-5b4b55fc9c-jv7pp
```

You will want to replace the instance name with your specific instance. See if you have this message:

```
'[haproxy.main()] Cannot raise FD limit to 80034, limit 65536.'
```

If so, you have run out of open file descriptors and as such the container cannot start.

---

Revision #4

Created 18 April 2022 12:27:02 by Karl Abbott

Updated 6 November 2024 12:49:16 by Kieran Mitchell Lane